

# Mobile Power

## KV-300 Watt DC TO AC POWER INVERTER

### Specification:

- Ac Out power 300W (Continuous power)
- Peak AC power: 600 W
- Ac Output Voltage : 230VAC
- Ac Output frequency: 50HZ+(-)3Hz
- Ac output waveform: Modified sine wave
- Dc input voltage: 12V(11v-15vdc) / 24V(22v-30vdc)
- No load current: 0.15A
- Dimension: 120x105x45mm(LxWxH)
- Weight: 0.8Kgs
- Fuse: 30A
- Efficiency: 90%
- Warranty: 1 Years
- Low battery alarm: 10.2-11.2v / 20.8-22.8v
- Low battery shutdown: 9.6v-10.6v / 19.6-21.6v

### Connection

- Battery Cigarette lighter
- Power out 1 piece 2 pole EU
- Remote ON/OFF Yes

### Overload protection:

- Short circuit protection
- Low battery alarm and Low battery shutdown
- Reverse protection by fuse
- High surge current capability easy to start TV, motors

