Allmendstrasse 6

Tel. +41 43 204 01 01 sales@exista.ch CH-8320 Fehraltorf Fax +41 43 204 01 02 www.exista.ch

let's talk!

# LAN-INV

Interface converter

## **Specification**

The interface converter LAN-INV offers an SNMP interface for the inverters of the INVP and INVB series. The device monitors up to 2 alarm contacts and transmits changes of relay status as SNMP traps. It measures the input voltage and the ambient temperature. All values can be sent via LAN interface and can additionally be presented via web interface.



Picture may differ from actual device

#### EMC

EMC emission	EN 55022, class B
EMC immunity	EN 55024

#### **Mechanical data**

Case material	Plastic
Protection class	IP 20
Dimensions	68 x 68 x 28 mm (WxHxD)
Weight	approx. 100 g

#### Connections

LAN interface

Warranty

24 months

9-pole

RJ45

D-SUB male connector,

**Order Code** 

LAN-INV

LAN LAN interface

Signals

General

interface

Input voltage

Power input

Electrical safety

Isolation of the LAN

**Electrical Data (input)** 

Relays

Temperature

Evaluation of two relay signals Measurement of the ambient temperature

EN 60950, VDE 0805

IEEE 802.3<sup>™</sup> compatible

10Base-T Port, supported network protocols: IPv4,

Ethernet Controller,

http, SNMP V1/V2c,

DHCP, NTP, ICMP

 $1.5 \text{ kV}_{AC}$ 

12 to 80 V<sub>DC</sub>

0.75 W

### **Environmental conditions**

Ambient temperature

-25°C to +60°C, non-condensing